CHAPTER – 27: SPECIFICATION FOR ACDB

SCOPE :

This specification covers design, manufacture, assembly, testing, at the manufacturer's works, supply, and delivery erection and commissioning of indoor type 415 Volts AC switch boards for the sub-stations as per approved schemes.

This also includes design, supply, laying and termination of XLPE insulated armoured power and control cables required for distribution of AC auxiliary power at different points of switchyard, control room building, colony and utility area, fire fighting pump house etc. for various purpose including Air conditioning system at control room, conference room and other places if mentioned in the technical specification of Air conditioning.

STANDARDS :

The equipment covered by this specification shall, unless otherwise specified, be in accordance with, relevant IS specification. The degree of protection shall not be less than IP-54 and IP-42 as per IS:2447 in case of bus bar chambers where continuous bus bar rating exceeds 1000 Amps.

DEVIATION :

Normally the offer should be as per Technical Specification without any deviation. . In case of any deviation taken against technical specification same are to be submitted in a separate deviation sheet for review of AEGCL.

MODIFICATION :

If any modification felt necessary to improve performance, efficiency and utility of equipment, the same must be mentioned in the 'Modification schedule' with reasons duly supported by documentary evidences and advantages. Such modifications suggested may or may not be accepted, but the same must be submitted along with Pre-Bid Queries. The modifications not mentioned in Schedule will not be considered.

DESIGN CRITERIA :

In case of 400KV sub-station, AC source shall be supplied separately from LT side of 2 numbers,1000KVA, 3/0.415KVstationservicetransformersthroughcable as per tender auxiliary SLD.

Two numbers 400 V/ 400 V Lighting Transformer with voltage variation arrangement atprimary side (in Off-load condition) in the range of ±5% in steps of 2.5%, shall be underscope of the bidder for supply, Erection, Testing & Commissioning for connection of Main of MainACDBwiththeMLDBpanel.RatingofLightingTransformersshallbeminimum100KV Afor400/220/132/33KVsub-station. One number, 100kVA shall be provided for connection to ELDB.However, rating may increase as per actual requirement keeping20%sparecapacity,which shall bewithinthescope of bidder.

The maximum loss component shall be guided as per relevant IS / IEC.

There shall be following panels designated as

MAIN ACDB – 2 Numbers

Sub ACDB – 2 Numbers

Main Lighting Distribution Board (MLDB) – 1 Number

Emergency Lighting Distribution Board (ELDB) – 1 Number

HVAC DB – 1 number

MCB DB – 1 number

All the above AC Panels shall be interconnected as per scheme layout.

Main ACDB: (415V)

Both the main AC Distribution board shall consist of the following items but not limited to this extent, within the scope of supply by Contractor with erection, Testing & Commissioning.

2000 A,4P Air Circuit Breaker and CT (of requisite rating) for 33/0.415 V station service transformers as INCOMER I for ACDB 1

2000 A,4P Air Circuit Breaker and CT (of requisite rating) for 33/0.415 V station service transformers as INCOMER II for ACDB 2

2 numbers 2000A, 4P Air Circuit Breaker along with 2 sets of CTs (of requisite rating) as Bus- coupler

Ammeters, voltmeters, energy meters, frequency meters, protective relays,fuses and all other equipment etc. required for complete operation shall be provided in the incomers.

PT shall be provided to measure the bus voltage alongwith relays.

Current, voltage and energy measurement shall be provided to SAS.

Bus bar shall be of copper with bus bar rating as 2000A, 25kA for 3 sec with adequate current density. Earth bus bar shall also be of copper.

Interlocks with DG set shall be provided as per requirement and the same shall be decided during detailed engineering.

The cable from station service to Main ACDB shall be 1.1kV, 1C, 1000sqmm, 2 runs for each phase and 1 run for neutral. The size of the cable may vary during detailed engineering.

All outgoing feeders shall be provided with ACB and MCCBs as required.

Sub ACDB: (415 V)

Incomer

Incomer from ACDB 1 to sub ACDB 1 and Incomer from ACDB 2 to sub ACDB 2 through MCCB and CT (of requisite rating)

Bus coupling between sub ACDB 1 and sub ACDB 2 through 2 nos MCCB and 2 nos CT (of requisite rating)

DG incomer (with AMF Panel) shall be connected to Sub ACDB-1 and Sub-ACDB -2

Ammeters, voltmeters, energy meters, frequency meters, protective relays (SC, O/L,E/F), fuses and all other equipment etc. required for complete operation shall be provided in the incomers.

PT shall be provided to measure the bus voltage alongwith relays.

Current, voltage and energy measurement shall be provided to SAS.

Bus bar shall be of copper with adequate bus bar rating with adequate current density. Earth bus bar shall also be of copper.

Interlocks shall be provided as per requirement and the same shall be decided during detailed engineering.

For all motor feeders shall be provided with all required protective relays.

All outgoing feeders shall be provided with MCCBs.

MLDB:

The MLDB (Main Lighting Distribution Board) shall consist of –

Two nos. 415 V Air Circuit Breaker as Incomer I & Incomer II from Main ACDB (through 2 nos. of Lighting transformers 400V / 400V, delta / star, Z% ~ 4.5, air cooled, dry type) and one no Air Circuit Breaker as Bus –Sectionaliser.

Current, voltage and energy measurement shall be provided to SAS.

Ammeters, voltmeters, energy meters, frequency meters, protective relays, fuses and all other equipments etc. required for complete operation shall be provided in the incomers.

Bus bar shall be of copper with adequate bus bar rating, with adequate current density. Earth bus bar shall also be of copper.

Interlocks shall be provided as per requirement and the same shall be decided during detailed engineering.

All outgoing feeders shall be provided with MCCBs.

ELDB: Emergency Lighting Distribution Boards

Two nos. 415 V MCCB as Incomer I & Incomer II from Main MLDB and one no MCCB as Bus–Sectionaliser. One Lighting transformer shall be provided for ELDB (415/415V, 50KVA).

Current, voltage and energy measurement shall be provided to SAS.

Ammeters, voltmeters, energy meters, frequency meters, protective relays, fuses and all other equipments etc. required for complete operation shall be provided in the incomers.

Bus bar shall be of copper with adequate bus bar rating, with adequate current density. Earth bus bar shall also be of copper.

Interlocks shall be provided as per requirement and the same shall be decided during detailed engineering.

All outgoing feeders shall be provided with MCCBs.

INTERLOCK LOGIC :

Electrical & Mechanical interlocking arrangement with Trip logic between the air circuit breakers of sub ACDB 1 and sub ACDB 2 and DG are tobe provided.

Interlocking of Incomer I & Incomer II with Bus Section Breaker:

Under normal condition (i.e. when supply is available through both the incomers), incomers I & II shall be in closed condition, Closing of Bus Coupler breaker shall be prohibited.

In case of failure of either of the sources, the incomer of that source shall trip through Under-Voltage relay and Bus coupler shall be allowed to close. After restoration, the respective incomer shall be allowed to close only after opening of Bus coupler breaker.

The above electrical interlock should be done through Breaker auxiliary contact switch.

Any other interlock logic shall be decided during detailed engineering.

A truth table and a load list shall be provided for all the distribution boards.

Interlocking of Incomer I & Incomer II of Sub-ACDB with DG-Incomer Breaker:

Under normal condition (i.e. when supply is available through both the incomers), incomers I & II shall be in closed condition, Closing of DG-Incomer breaker shall be prohibited.

In case of failure of either of the sources, the incomer of that source shall trip through Under-Voltage relay and Bus coupler shall be allowed to close, but Closing of DG-Incomer breaker shall be prohibited.

In case of failure of supply of both the incomers, both the incomer alongwith bus coupler shall trip through Under- Voltage relay and DG set breaker shall be allowed to switch on. After restoration, the incomer breakers shall be allowed to close only after opening of DG set breaker. Time delay relay shall be used to obtain the interlock logic.

The above electrical interlock should be done through Breaker auxiliary contact switches.

The interlock schemes may be modified during detailed engineering as per AEGCLs requirement and ease of operation.

TYPICAL FEEDER DISTRIBUTION OF SUBSTATION:

GENERAL (Exact Quantity will be finalised at the time of Detailed Engineering and within the scope of bidder. Generally, MCCB shall be considered. In case of exigency, SFU can be used by taking prior written approval from AEGCL approving engineer.): Cable sizes shall be considered as per the load.

INTERCHANGEABILITY :

All similar material and movable parts shall be interchangeable with each other. Such as the breakers, switches, contactors etc. shall be easily removable as a complete unit from the switch boards and shall be capable of being put into similar position in other switch boards for performing identical function.

CONSTRUCTION :

The switch boards shall be of multi-cubicle or multi box factory-built air-insulated type, fully enclosed with doors for access to the interior. 3.00 mm. thick steel sheet shall be used for the fabrication of the panels. Boards shall be easily extendible on both sides, by the addition of the vertical section after removing the end covers.

The complete panels shall not be more than 2450 mm. high with the channel base and the depth shall be preferably within 1000 mm. wide measured from rear to front faces. The working height shall be minimum 450 mm. to maximum 2000 mm. The width of the panel shall depend upon the no. of circuits to be accommodated.

All boards shall be divided into distinct vertical sections each comprising of :

A completely enclosed bus bar compartment for running horizontal and vertical COPPER bus bars. Bus bar chamber shall be completely enclosed with metallic portions. Bolted covers shall be provided for access to horizontal and vertical bus bars and all joints for repair and maintenance, which shall be feasible without disturbing feeder compartment. Proper ventilation arrangement shall have to be arranged and that shall be decided by the purchaser at the time of approval of drawings

Completely enclosed switchgear compartments one for each circuit for housing Air circuit breaker or SFU or MCB or MCCB or motor starter.

A compartment for power and control cable. Door of compartment shall be hinged. Cable compartment shall have no communication with bus bar chamber.

A compartment for relays and other control devices associated with a circuit breaker. The panels shall be designed to facilitate cable entry from the bottom through entry holes of removable gland plates provided at the bottom of the cubicle. All the accessories required for terminations of cables in the ACDB such as cable gland, terminal block etc. shall be within the scope of supply.

Doors shall have pad locking facilities.

After isolation of power and control circuit connections it shall be possible to safely carry out maintenance in a compartment with the bus bar and adjacent circuit live. Necessary shrouding arrangement shall be provided for this purpose over the cable terminations located in cable alley.

In case of providing two incomers air circuit breaker in the same vertical section, insulating barriers and shroud shall be provided in the rear cable compartment in order to avoid accidental touch with live parts of one circuit when working on the other circuit.

The connections from bus bars to main switch shall be fully insulated/shrouded and securely bolted. The partition between the feeder compartment and cable alley may be non-metallic and shall allow cables cores with lugs to be easily inserted in the feeder compartment for termination.

The switch board shall be dust proof, vermin proof, rodent proof and suitable for use in tropical climate. All ventilating louvers and holes shall be covered with fine wire mesh from inside. Necessary pre-treatmentof the panel surface is to be done by seven tank process followed by 2 coats of polyurethane/enamel paint. The colour of the exterior of the panel shall be RAL-7032 as that of the main control and relay panel. The colour of the interior panel should be as to provide a colour contrasting background for the wiring Inside the cubicle.

The switchboards shall be mounted on channel and shall be complete with channel bottom plates made of structural steel, grouting bolts, earthing bolts, washers, cable glands etc.

Both the single and three phase switches as well as the fuse terminals provided on the panel shall be of best quality and easy in operation.

The tentative entries of power and control cable shall be from bottom.

Adapter panels and dummy panels required to meet the various bus bar arrangements and layout required shall be included in Bidder’s scope of works.

All modules shall be fixed type except air circuit breaker module which shall be draw out type. All disconnecting contacts for power circuits shall be of robust design and fully self-aligning.

Fixed and moving contacts of the power draw out contact system shall be silver-plated and both fixed and moving contacts shall be replaceable. Silver plating shall not be less than 25 microns.

All Distribution Boards shall be single front type.

All single front board shall be provided with removable bolted covers at the rear. The covers shall be provided with danger levels.

Sheet steel barriers shall be provided between two adjacent panels running to the full height of the switch board, except for the horizontal bus bar compartment.

POWER BUS BARS AND INSULATORS

Bus bars shall be of Copper, liberally sized for the specified continuous current rating as per approved scheme and short circuit current rating of 50 KA (rms) for 3 sec. Necessary precaution shall be taken to avoid bimetallic action. Means shall be provided for identifying various phases of bus bars by red, yellow and blue paint. The cross section of the bus bars shall be uniform through out the length of switch gear.

Bus support shall be of arc resistant, non-tracking, low absorption type installations of high impact strength to withstand normal as well as fault condition stresses.

EARTH BUS : A copper earthing shall be provided at the bottom of each panel and shall extend through out the length of switchboard. It shall be welded/bolted to the frame work of each panel and breaker earthing contact bar. Vertical bus shall be provided in each vertical section which shall in turn be bolted/welded to main horizontal ground bus. Bimetallic connection shall be provided to connect the earth bus with the main substation earth bus.

The earth bus shall have sufficient cross section to carry momentary short circuit and short time fault currents to earth bus without exceeding the allowable temperature rise.(Preferably 65x12 or higher as per calculation)

The horizontal earth bus shall be projected out of the switch board ends and shall have pre-drilled holes for bolted connection between this bus to sub-station earthing conductor. A joint spaced and taps to earth bus shall be made through at least two bolts.

All non-current metal works of the switch board shall be effectively bonded to the earth bus.

AIR CIRCUIT BREAKERS : (For two incomers and bus sectionaliser of ACDB and DG)

Incoming and Bus sectionalizer air circuit breaker shall be four pole air break horizontal draw out type and shall have inherent fault making and breaking capacities as per requirement. All the poles of circuit breakers shall open and close simultaneously. The neutral pole shall be 100% rated.

Circuit breakers shall be mounted along with it operating mechanism on a wheeled carriage. Suitable guides shall be provided to minimise misalignment of the breaker.

There shall be ‘Service’, ‘Test’ ‘ISOLATED’ and ‘MAINTENANCE’ positions for the breakers. In ‘Test’ position the circuit breaker shall be capable of being tested for operation without energising the power circuits i.e. the power Contacts shall be disconnected while the Control circuits shall remain undisturbed. Locking facilities shall be provided so as to prevent movement of the circuit breaker from

the ‘SERVICE’, ‘TEST’. It shall be possible to close the door in ‘TEST’ position.

There should be provision for locking the air circuit breaker in ‘ISOLATED’ position to achieve mechanical interlocking with Incomer & Bus sectionalizer Air Circuit Breakers.

All circuit breakers shall be provided with 8 NO and 8 NC potentially free auxiliary contacts with additional 20% spare. These contacts shall be in addition to those required for internal mechanism of the breaker. Separate limit switches each having required number of contacts shall be provided in both ‘SERVICE’ & ‘TEST’ position of the breaker. All contacts shall be rated for making continuously carrying and breaking 10 Amps at 240 V AC and 2 Amp at 220 V DC.

Suitable mechanical indications shall be provided on all circuit breakers to show ‘OPEN’, ‘CLOSE’, ’SERVICE’, ‘TEST’, ISOLATED and ‘SPRING CHARGED’ positions.

Movement of a circuit breaker between SERVICE AND TEST positions shall not be possible unless it is in OPEN position. Racking interlock for this shall be provided.

Closing of a circuit breaker shall not be possible unless it is in SERVICE, TEST POSITION or in FULLY WITHDRAWN POSITION.

Circuit breaker cubicles shall be provided with safety shutters operated automatically by the movement of the circuit breaker carriage to cover the stationary isolated contacts when the breaker is withdrawn. It shall however, be possible to open the shutters intentionally, against spring pressure for testing purpose.

A breaker of particular rating shall be prevented from insertion in a cubicle of a different rating. The ACB’s shall have rating error preventor to achieve this.

Circuit breakers shall be provided with electrical anti-pumping and trip free feature even if mechanical anti-pumping feature is provided.

Mechanical tripping shall be possible by means of front mounted RED ‘Trip’ push-button. In case of electrically operated breakers these push-buttons shall be shrouded to prevent accidental operation.

Power operated mechanism shall be provided with a universal motor suitable for operation 220V DC Control supply with voltage variation from 85% to 110% rated voltage. Motor insulation shall be class ‘E’ or better.

Once the closing springs are discharged, after the one closing operation of circuit breaker, it shall automatically initiate, recharging of the spring. The motor shall be such that it requires not more than 30 seconds for fully charging the closing spring.

The mechanism shall be such that as long as power is available to the motor, a continuous sequence of closing and opening operations shall be possible. After failure of power supply at least one open-close-open operation shall be possible.

Provision shall be made for emergency manual charging and as soon as this manual charging handle is coupled, the motor shall automatically get mechanically decoupled.

All circuit breakers shall be provided with closing and 2 trip coils. The closing coils shall operate correctly at all values of Voltage between 85% to 110% at rated control voltage. The trip coils shall operate satisfactorily under all values of supply voltage between 70% to 110% of rated control voltage Trip ckt supervision shall be provided for both the trip coils.

The door of the circuit breaker compartment shall be interlocked so that (1) door cannot be opened while the breaker is in closed position and (2) when the door is open the breaker cannot be closed. However, facility to defeat this interlock shall be provided for testing purpose.

Provision for mechanical closing of the breaker only in ‘TEST’ and ‘WITHDRAWN’ positions shall be made.

Air Circuit Breakers shall be from one of the following manufacturer’s complying with technical specification & relevant IS & IEC

M/s Siemens

M/s L & T

M/s ABB

M/s Schneider

M/s GE

SWITCH FUSE UNIT (SFU), MOULDED CASE CIRCUIT BREAKER (MCCB) AND (MCB)

SFU / MCCB shall be 4 pole /2 pole, capable of safely breaking the fault current of the associated feeder. Rating of SFU / MCCB’s shall be chosen by the contractor depending upon requirement of outgoing feeders and as decided in detailed engineering stage and shall be subject to approval of AEGCL.

All the SFU / MCCB shall be flush mounted on AC Distribution boards provided with Rotary operating handle with clear ON-OFF trip indication.

MCCBs shall be provided with thermo-magnetic type release for over current and short circuit protection. The o/c setting shall be adjustable type. The s/c settings shall be adjustable type.

The setting range of thermal release and breaking capacity of MCCBs are to be specified and shall conform to system requirement. MCCB Knob shall indicate the true position of the equipment. MCCBs shall conform to relevant Indian Standard IS : 13947 Part 2 and shall be of P2 duty.

AC switch board shall be installed in a separate ACDB room other than control room for 400/220/132/33KV S/stn. For tripping of any of the outgoing feeder, visual and audible alarm arrangement shall be provided in the AC Board. However arrangement has to be made for getting audible alarm at the control room for the knowledge of the operator regarding tripping of the outgoing feeders. Necessary arrangement shall also be provided for acceptance and resetting of the audible alarm. In case of tripping of Incoming feeder breaker or Bus sectionalizing breaker, arrangement of both audible and visual annunciation shall be made both at AC Board as well in Control room. Acceptance and resetting arrangement is to be provided.

Interlocks shall be provided such that it is possible to open the cubicle door only when the SFU / MCCB/MCB is in 'OFF' position and to close the SFU / MCCB/MCB when the door is closed.

Miniature Circuit Breaker (MCB) shall conform to IEC:898-1987 and IS:8828.

SFU, MCCB & MCB shall be from one of the following manufacturer's complying with technical specification & relevant IS & IEC

M/s Siemens

M/s L & T

M/s ABB

M/s Schneider

M/s GE

In this project, MCCBs and MCBs shall only be used. MCBs shall be used below 15A.

CONTROL AND SELECTOR SWITCHES :

Control and Selector switches shall be rotary type with escutcheon plates clearly marked to show the junction and positions. Switches shall be of sturdy construction suitable for making on panel front.

Voltmeter selector switches shall have four stay put position with adequate no. of contacts for 3-phase 4-wire system. These shall be oval handles. .

Contacts of the switches shall be spring assisted and shall be of suitable material for giving long trouble free services.

Contact ratings shall be at least the followings :

Make and carry continuously : 10 Amp.

(ii) Breaking current at 240VAC :4KA (at 0.3 p.f.lagging)

AIR BREAK SWITCHES :

Air breaker switch shall be of heavy duty, single throw group operated, load break, fault make type complying IS:4046.

Switch operating handles shall be provided with pad locking facilities to lock them in 'OFF' position.

All switches shall be adequately rated so as to be fully protected by the associated fuses during all abnormal conditions such as over load, locked motor, short circuit etc.

Interlock shall be provided so that cubicle door can only be opened when the switch is in 'OFF' position and to close the switch only when the door is closed. However, suitable means shall also be provided to intentionally defeat the interlocks as mentioned above.

Switches and fuses MCCB/MCB for AC control supply and heater supply wherever required shall be mounted inside the cubicles.

INDICATING LAMPS OF CONTROL SWITCHES :

Indicating lamps shall be of the panel mounting cluster LED type. The lamps shall have suitable size plates marked with its function, wherever necessary.

Lamps shall have translucent lamp covers of the following colours.

RED	Breaker Closed.
GREEN	Breaker Open
WHITE	Breaker Auto-Trip
BLUE	For all healthy condition. (e.g. Control supply and also for "SPRING CHARGED" and "TRIP CIRCUIT HEALTHY")
AMBER	For all alarm conditions (e.g. overload).

Separate indication lamps for ‘SERVICE’, ISOLATED and ‘TEST’ positions shall be provided.

SPACE HEATERS :

Space heaters shall be provided for preventing harmful moisture condensation in all the AC Boards. The space heaters shall be suitable for continuous operation on 240 V AC,50 HZ,1-phase supply and shall be automatically controlled by thermostats. Necessary isolating switches and fuses shall also be provided.

INTERNAL WIRING AND TERMINAL BLOCK :

All switch boards shall be supplied completely wired internally upto the terminal blocks.

All inter cubicle and inter panel wiring and connections between panel of same switch board including all bus wiring for AC and DC supplies shall be provided by the contractor.

All internal wiring shall be carried out with XLPE insulated, stranded copper conductor, 1.1kV, single core, 2.5 sq. mm. or larger stranded copper wires. CT Ckts. shall be wired with 4 sq. mm. voltage grade and insulation of copper wires shall be same as above. Voltage drop shall be allowed only in the tune of 3% at the remote end of the longest outgoing feeder from the AC Panel board and 15% drop in case of starting of motor of the remote end.

All wiring shall be properly supported, neatly bunched, readily accessible and securely connected to equipment terminals and terminal blocks.

Each wire shall be identified at both ends and shall be properly tagged and ferruled in compliance with approved drawings. Wires shall not be spliced or tapped between terminal points.

Terminal blocks shall be of 1100 V grade ‘Elmex/connect well’ make and have continuous rating to carry the maximum expected current on the terminals. The terminal blocks shall be fully enclosed with removable covers of transparent, non-deteriorating type plastic material. Insulating barrier shall be provided between the terminal. The terminal blocks shall have locking arrangement to prevent its escape from the rails. 30% spare terminals are to be provided on all terminal blocks.

Terminal blocks for CT secondary leads shall be provided with test links and isolating facilities. CT secondary leads shall be provided with short circuiting and earthing facilities. Jam nut should be provided with shorting link.

All terminal blocks shall be normally suitable for terminating on each side, two (2) nos. of

2.5 mm. sq. size stranded copper conductor. However, terminal blocks to be used in conjunctive with CT shall be suitable for terminating 4 sq. mm. single core Copper wires.

All terminals shall be ring type and numbered for identification and grouped according to the function. Engraved white on-black labels shall be provided on the terminal blocks.

Terminal blocks shall be arranged with at least 200 mm. clearance between two sets of terminal block. The minimum clearance between the first row of terminal block and the associated cable gland plate shall be 250mm.

POWER CABLE TERMINATIONS :

Cable termination compartment and arrangement for power cables shall be suitable for stranded copper Conductor, armoured XLPE insulated and sheathed 4 / 3.5 -core, 1100V grade.

All necessary cable terminating accessories such as Gland plates, supporting clamps and brackets, power cable lugs, hardware etc. shall be provided by the contractor to suit the final cable sizes.

The gland plate shall be of removable type and shall cover the entire cable alley. Bidder shall also ensure that sufficient space is provided for all cable termination.

GROUNDING :

An copper strip ground bus rated to carry maximum fault current for the specified duration shall be provided along the entire length of the distribution board.

Each casing of the equipments, relays, instruments provided in the board shall be connected directly to the ground bus by independent stranded copper wires of not less than 2.5 sq. mm. The earth bus shall have sufficient cross-section to carry the momentary short circuit and short time fault currents to earth without exceeding the allowable temperature rise. The ground bus shall be brought out to two terminals at the two ends of the switch board for Connecting G.S. Flat of 65×12mm for all voltage classes. CT & PT secondary neutral point shall be at one place only on the terminal block. Such earthing shall be made through links.

TROPICAL FINISH :

All electrical equipment, accessories and insulation of wiring shall have fungus protection involving special treatment on insulation and metal against fungus, insect and corrosion.

INSULATION :

The insulation at any point in the distribution board shall be of 1.1 KV grade.

ASSOCIATED EQUIPMNET AND ACCESSORIES:

CABLE GLANDS :

All feeders shall be provided with suitable dust tight screwed brass double compression cable glands conforming to the relevant IS standard.

Gland shall project above the gland plate. Terminating cables shall be armoured and the armour rods shall be connected to earth bar.

METERS :

The accuracy class of Electronic type KWH meter shall be 0.2. One KWH meter of 3-phase, 4-wire type shall be flush mounted on each of the incoming breaker compartments of Main ACDB/DG, Ammeter and voltmeter shall be of 72*144sq.mm and of flush mounting digital type with accuracy +/- 1% of full scale. The meters shall conform to the appropriate IS specification. All circuitsof the meters shall be capable of withstanding 20% overload for a period of at least 8 hours.Three no. digital Ammeter and one no digital Voltmeter shall be provided for each incoming CB's of Main ACDB/Sub ACDB's with voltmeter selectors with and ammeter selector switch.

NUMERICAL RELAYS :

All the protections shall be of numerical type (shall be as per make list) and supported by Test Certificates from Govt. recognized Test house and performance certificates from Govt./Power Utilities.

The relay shall have –

Minimum two characteristics, one IDMT of 3 sec. and the other one of definite time characteristic and the same should be site selectable.

Wide range of time and current setting in very small steps without sacrificing the relay characteristics.

Tripping indication for different type of faults until reset by the operator.

Continuous self supervision along with self diagnostic feature for faults within the relay and the relay should have potential free 'Change over Contact' for annunciation in the event of internal failure.

Output contacts having sufficient current rating to directly energise trip coil of circuit breaker.

LED indication facility for visual annunciation of different type of faults including phase identification.

Individually site selectable binary Output and Input and latching option for binary Output.

Motor starters shall be provided with ambient temp. compensated, time lagged, hand reset type over load relays with adjustable settings ranges to suit motor ratings. These relays shall have separate black coloured hand reset push button mounted on compartment door and shall have at least one changeover contact.

INSTRUMENT TRANSFORMER (FOR 400/220/132/33KV SUBSTATION) :

All current and voltage transformers shall be completely encapsulated cast resin insulated wound type suitable for continuous operation at the temperature prevailing inside the switch gear enclosures, when the switch board is operating at its rated condition and the outside ambient temperature is 50oC.

All instrument transformers shall be able to withstand the thermal and mechanical stresses resulting from the maximum short circuit.

All instrument transformers shall have clear indelible polarity markings.

The insulation level of C.T shall be suitable for 1.1 KV grade. C.T. for 400KV portion shall be 2500/1A, 3 core type of which one core for metering and second core for protection. The third core of the C.T shall be used for REF protection and particulars shall be 20 VA, 5P20. The REF relay shall be mounted in the 33 KV C & R panel and the respective LT side phase C.T cores for REF protection shall be terminated to the terminal block of the AC panel.

All voltage transformers shall have readily accessible HRC current limiting fuses on both primary and secondary sides.

NAMEPLATES AND LABELS :

ACDB shall be provided with prominent, engraved anodized identification plates. The module identification plate shall clearly give feeder number and feeder designation. For single front switchboards, similar panel and board identification labels shall be provided at the rear also.

All name plates shall be non-rusting metal or 3-ply lamicold with white engraved lettering on black base ground. Suitable plastic sticker labels shall be provided for easy identification of all equipments, located inside the panel / module. These labels shall be positioned so as to be clearly visible and shall give device number as mentioned in the module wiring.

PACKING AND DESPATCH :

All equipments shall have to be dispatched suitably and securely packed in wooden crates, suitable for handling during transit by rail and / or road.

CONTRACT DRAWING & CATALOGUE :

A. After placement of Letter of Award four (4) copies of following drawings, GTP and literature shall be submitted to the AEGCL for approval :

i) Single line diagram of each AC Board.

ii) General Arrangementdrawingshowingdimensionsoffrontandrearvi ewofeachswitch board with relay instruments and other devices position marked. Height, width, depth and ground fixing arrangement shall have to be indicated.

iii) Schematic wiring diagram for each switchboard.

iv) Catalogue on each type of circuit breaker, MCCB, switches, fuse, relays, meters etc. offered. The list of drawing shall be furnished in the schedule attached herein.

TESTS AT MANUFACTURER'S WORKS AND TEST CERTIFICATES :

Acceptance and routine test at manufacturer's works shall be carried out on each AC Board as per stipulation of relevant Indian Standard. The entire cost of acceptance and routine tests are to be carried out shall be treated as included in the quoted price of all Distribution Board.

All the acceptance and routine tests shall be carried out in presence of representative of AEGCL. Three (3) copies of test reports shall be submitted to the AEGCL for approval and distribution to site.

The Contractor shall give at least 15 (fifteen) days advance notice intimating the actual date of inspection and details of all tests that are to be carried out.

GUARANTEE :

Electrical characteristic shall be guaranteed by the bidder. In case of failure of materials to meet the guarantee, AEGCL shall have right to reject the material. Guaranteed Technical Particulars are to be submitted by successful bidder during detailed engineering along with submitted drawings/documents. However format for submission of GTP shall be handed over to intending bidders at the time of Sale of tender document.

SPECIFIC TECHNICAL PARAMETERS OF AC DISTRIBUTION BOARDS

The following particulars are to be complied with :

SL NO	DESCRIPTION	TECHNICAL PARAMETERS	
1.	DIMENSIONS :		
	i)	Height of complete panel (mm)	2450 (Max.)
	ii)	Working height (mm)	450 (Min.) to 2000 (Max.)
	iii)	Depth (mm)	1000 (Max.) for outgoing panel & 1500 (Max) for Air C.B. panel.
	iv)	Length of the panel (mm)	As per requirement
2.	Sheet steel thickness of Panel (mm)	3 (Min.)	
3.	Insulation Level of Equipments and Wiring (KV)	1.1	
4.	Minimum Rating of Fuses (Amps.)	Not less than 16	
5.	Spring operated Air Circuit Breaker/ SFU / MCCB fault current breaking Capacity (KA)	50	
6.	Voltmeter Range / Rating (Volts)	0 to 500	
7.	Ammeter Range with Current Transformer (Amps)	As per requirement. Shall be decided during detailed engineering	
8.	LT AC AIR CIRCUIT BREAKER :		
	i)	System Voltage	400 V AC +/- 10%
	ii)	Insulation Voltage	1.1 KV 1.2
	iii)	Rated Imp withstand voltage of main CktUimp	8 KV
	iv)	Rated Imp withstand voltage of Aux CktUimp	4 KV
	v)	Ambient Temperature	50oC
	vi)	Rated frequency	50 Hz

SL NO	DESCRIPTION	TECHNICAL PARAMETERS	
	vii)	Rated Continuous Current at 50oC	2000A for 1MVA transformer
	viii)	a) Ultimate Short Ckt Breaking Capacity Icu	50KA
		b) Service Short Ckt Breaking Capacity Ics	100% of Icu
		c) WithstandShortCktBreaking Capacity Icw	50 KA for 1 Sec
		d) Rated Making Capacity Icm	105 KA
	ix)	Utilisation Category	B
	x)	Suitable Isolation	Yes
	xi)	No. of Poles	4 Pole
	xii)	a) Opening Time	40-60 ms
		b) Closing Time	60-80 ms
	xiii)	Type of Breaker	Electrical Draw Out
	xiv)	a) Spring Charging Voltage	230 V AC/220V DC
		b) Permissible Variation in Voltage	85% to 110%
		c) Spring Charging Time	7-10 Sec
	xv)	a) Closing Coil Voltage	220 V DC
		b) Permissible Variation in Voltage	85% to 110%
	xvi)	a) Tripping Coil Voltage	220 V DC
		b) Permissible Variation in Voltage	70% to 120%
	xvii)	a) Mechanical Life	20,000
		b) ElectricalLifewithmaintenance (changing arcing Contracts)	20,000
	xviii)	Termination suitable for Aluminium as per IS 13947 Part-II	Yes
	xix)	Insulation Material conforming to Glow Wire Test	Yes
	xx)	Mechanical Interlock for Incomer & Bus Coupler	Yes via Castel Lock
	xxi)	Rated duration of Short Circuit Current	3 Sec
	xxii)	MaximumTemperatureriseabove Ambient at Rated Current	50oC
	xxiii)	Rated Operating Duty	O – 0.3 Sec – CO – 3 Min – CO
	xxiv)	Rated Short Circuit Breaking Capacity	30 MVA
9.	BUSBAR :		
	i)	Rated	As required.
	ii)	Short circuit withstand current	50KA(rms)for400KV substation, 40KA (rms) for 220 & 132KV substation
	iii)	Duration of Short Circuit	3 second
	iv)	Rupturing withstand current	106.56 (peak) KA
	v)	Temp. rise above ambient at rated current	50oC
	vi)	Made of Aluminium of current density not higher than	As per requirement
	vii)	Insulation voltage	1.1KV
10.	SWITCHES (SFU / MCCB) :		
	i)	System Voltage	415 V AC ± 10%
	ii)	Insulating Voltage	1.1 KV
	iii)	Rated Imp withstand Voltage of main CktUimp	8 KV
	iv)	Ambient Temperature	50oC
	v)	Rated Frequency	50 Hz
	vi)	Rated Continuous Current at 50oC	As per Rating
	vii)	Ultimate Short Ckt Breaking Capacity Icu	35 KA
		Service Short Ckt Breaking Capacity Ics	100% of Icu

SL NO	DESCRIPTION	TECHNICAL PARAMETERS	
	viii)	Utilisation Category	A
	ix)	Suitable for Isolation	Yes
	x)	No. of Poles	4 Pole or 2 Pole – as per requirement
	xi)	a) Shunt Release Voltage	220 V DC
		b) Permissible Variation in Voltage	85% to 110%
	xii)	Termination suitable for Aluminium as per IS 13947 Part-II	Yes
	xiii)	Insulation Material conforming to Glow Wire Test	Yes
	xiv)	Thermal Over load Settings	Adjustable
	xv)	Short Circuit Setting	Adjustable for 4 Pole and Fixed for 2 Pole
11.	FUSE :		
	i)	Type	HRC
	ii)	Rupturing current	Less than breaker rupturing current
	iii)	Maximum rise of temperature at rated current fuse above ambient	50oC
	iv)	Link base	Mode of porcelain equivalent element

N.B. The outgoing feeders are meant for A.C supply to different control panel, protection panel, Battery charger, PLCC equipment, etc and Transformer auxiliary supply, CB/Isolator auxiliary supply, switchyard lighting, water supply, air conditioning system at control room building, fire fighting system, oil filtration and other auxiliary supply related to 400/220/132 KV sub-station.

The successful bidder is to supply AC distribution board to be finalized as per requirement during detailed engineering and as per approved drawings, which shall be within the scope of bidder.

27.14 Catalogue of all relays with characteristic curve shall be submitted with tender documents.

27.15 Sub Vendor List for ACDB

Sl No.	PRODUCT	MAKE
1	METERS DIGITALANDANALOGUEAMMETER,VOLTMETER,	MECO,SECURE,RISHABH, VAISHNO
2	KWHMETER	L&T, SECURE, RISHABH
3	FREQUENCYMETER	RISHABH, MECO, VAISHNO
4	FUSE FITTING &FUSELINK	COPPERBUSHMANN, ABB,SIEMENS, L&T, GE
5	TRANSDUCERSVOLTAGETRANSDUCER,CURRENTTRANSDUCER,FREQUENCY TRANSDUCERETC.	ELSTER, RISHABH, SIEMENS
6	CONTACTORS	L&T, SIEMENS, SCHNEIDER,GE, ABB
8	PROTECTION AND OTHER RELAYS	ABB,GE,SIEMENS,Schneider
7	SFU, MCCB,	GE, ABB, L&T, SIEMENS, LEGRAND, SCHNEIDER
8	MCB,	SCHNEIDER,LEGRAND,ABB, SPRECHER &SCHUH(S&S)
9	CT	C&S, KAPPA, GILBERTMAXWELL, ABB,PRAGATI, GE, BHEL,SIEMENS
10	PT	C&S, KAPPA, GILBERT MAXWELL, CGL
11	LTCONTROLSWITCHESAMMETER, VOLTMETER SELECTOR SWITCHES, BREAKER CONTROL SWITCHES,ROTARY CAM/ROTARYSWITCH	KAYCEE, RECOM, SWITRON, VAISHNO, GE, ABB
12	ANNUNCIATOR,HOOTER,BUZZER, ELECTRONIC BELL.	PROTON,MINILEC,ALAN, VAISHNO.,PROCON,PIRI
13	TERMINAL BLOCK,TERMINAL END PLATE	ELMEX, CONNECTWELL
14	SPACE HEATER	SOFIA,GIRISH(EGO), VIKASELECT., GIRISH, APTCONTROL,KONTACT PYROS, TELELEC,HOTWELL,
15	THERMOSTAT	GIRISH(EGO),VIKASELECT., APTCONTROL,KONTACTPYROS
16	PANELTUBE FIXTURE,CHOKE, STARTER,ILLUMINATION LAMP	PHILIPS,BAJAJ
17	3PIN SWITCH SOCKET(INDUSTRIAL/SERVICE)/RECEPTACLE	ANCHOR, CGL,SCHNEIDER, LEGRAND,ABB

Sl No.	PRODUCT	MAKE
18	BUS BAR SUPPORTINSULATOR	RAMANUJ,POWERMAT,VINAYAK,SUNINSULATOR, TECHNO, ESBEECONTROL
19	PVC/FRLSWIRE	KEI, POLYCAB, FINOLEX
20	LUGS	DOVELLS,COMET,JAINELECTRONICS,SJMETAL
21	HARDWARE MS&SS	TVS,KUNDAN,AGRWALFASTENERS,FITRIGHT
22	POWER PACKS	ALAN
23	INDICATING LAMP/LED,FILLAMENT LAMP	L&T, GE,SIEMENS, SCHNEIDER
24	PUSHBUTTONS WITH ELEMENTS	L&T, ABB,SIEMENS
25	ELECTRONICTIMER	L&T, GE, ABB, SCHNEIDER,SIEMENS
26	RUBBERGASKET (NEOPRINE/EPDM)	MINERVARUBBER&ENGG IND.,HANUIND., JSONPOLYMER, RITTAL,R K PROFILE, ASP MINERVA, RKPROFILE
27	M.S.CRCA/HRCASHEETS/COILS	TATA,SAIL,ESSAR
28	ALUMINIUMBUSBAR	SUDAL,HINDALCO,JINDAL, BALCO
29	COPPER BUSBAR	VIJAY IND., NEW INDIA CUPROTEC, CUBEXTUBING LTD (HYDERABAD).,ALCOBEXJODHPUR(MUMBAI),,MODISONMETAL,CITIZENMETALLOYS(AHMEDABAD), RHJ EXTRUSION(DAMAN)
30	LIMITSWITCH/DOORLIMIT SWITCH	KAYCEE,RECOM,SIEMENS, VAISHNO, L&T
31	ALLUMINIUM SHEET/STAINLESSSTEELSHEET/COILS	ESSAR,BALCO, HINDALCO, SAIL, TATA
32	OIL & WINDINGTEMPERATURE INDICATOR	PRECIMEASURE,PERFECT CONTROL(CHENNAI)
33	AIR CIRCUITBREAKER(ACB)	L&T, GE, ABB, SCHNEIDER,SIEMENS
34	TIMESWITCH	L&T, GE, ABB, SCHNEIDER, SIEMENS
35	2POLEAC/DCSWITCH	GE, SCHNEIDER
36	LIGHTINGTRANSFORMER	INDCOIL, GUJARATPLUGIN,LOGICSTAT

GUARANTEED TECHNICAL PARTICULARS FOR 400/230 VOLTS A.C. POWER DISTRIBUTION SWITCHBOARDS

(To be filled in and signed by the Bidder)

1	ACDB GENERAL	
1.01	Name of Manufacturer	
1.02	Location of the Factory	
1.03	Date of Last Type Test Done	
1.04	Conforming Standard	
1.05	Type & Model of the ACDB as per Manufacturer	
1.06	Dimension of Panel (L x B x H) -mm	
1.07	Total Number of Incoming& Outgoing Compartment	
2	Bus-Bar Material	
2.1	Dimension (Width x Thickness) -mm	
2.2	Continuous Current Rating in Amps	
2.3	Current density (Amp/Sq.cm.)	
3	Air Circuit breaker	
3.01	Manufacturer	
3.02	Type & Model as per manufacturer	
3.03	Conforming Standard	
3.04	No of Poles	
3.05	Opening / Closing Time (ms)	
3.06	Current	
3.06.1	Rated continuous current carrying capacity in Amps	
3.06.2	Rated SC Current at 415 V (KA rms)	
3.06.3	Making capacity	
3.06.4	Rated SC Breaking Current at 415 V (KA rms) capacity	

1	ACDB GENERAL	
3.06.5	Short time ratings for 1 sec.	
3.07	Voltage	
3.07.1	Rated Voltage	
3.07.2	Basic Insulation Level	
3.07.3	Closing/Tripping Coil Voltage	
3.08	Maximum temperature rise above ambient temperature of 50oC	
3.09	CT provided with ACB	
3.09.1	Manufacturer	
3.09.2	Type as per manufacturer	
3.09.3	Number of Core	
3.09.4	Ratio	
3.09.5	VA burden	
3.09.6	Accuracy class	
3.09.7	Type of insulation	
4	Fuse Switch Unit / Switch Disconnctors	
4.01	Manufacturer	
4.02	Type/ Model as per manufacturer with number of Poles	
4.03	Conforming Standard	
4.04	Voltage	
4.04.1	Rated Operational Volatge without derating	
4.04.2	Insulation Volatge	
4.04.3	Impulse Withstand Voltage	
4.05	Current	
4.05.1	Operational Current	
4.05.2	Conventional enclosed Thermal Current rating at 45 0 C	
4.05.3	AC 23 A Utilisation Category Rating at 415 V (A)	
4.05.4	DC 23 A Utilisation Category Rating at 220 V DC (A)	
4.05.5	Rated AC Making Capacity at 0.35 pf	
4.05.6	Rated AC Breaking Capacity at 0.35 pf	
4.05.7	Rated DC Making Capacity / DC Breaking Capacity at 220 V, L/R 15 ms	
4.05.8	Rated Conditional Fused SC Current (KArms)	
4.05.9	Back-up Fuse rating	
4.05.10	Maximum Cut Off Current permitted (Kap)	
4.05.11	Rated AC Capacitor Power (KVAr) at 415 V AC	
4.05.12	Mechanical Endurance Cycle (number)	
4.05.13	Electrical Endurance Cycle at 0.65 pf (number)	
4.05.14	Auxilary Contact Thermal rating (A)	
5	A.C. Meters / Energy Meters (Details for Ammeters, Voltmeters, Energy-meters shall be furnished separately)	
5.01	Manufacturer	
5.02	Type	
5.03	Range	
5.04	Accuracy	
5.05	Conforming Standard	